SyncScan 3

64:128PR Phased Array Flaw Detector with TFM



















MOPE Possibilities

Advanced Solutions for Welds & Corrosion






SyncScan 3

Phased Array Flaw Detector with TFM


More Possibilities for Demanding Inspection

SyncScan 3 is 64:128PR PAUT flaw detector with total focusing method (TFM) and 4-ch TOFD, which brings more possibilities for demanding inspections in oil & gas, power industries, etc.

- TFM image resolution up to 1024×1024.
- 64-ch PA with higher sensitivity and SNR, ideal for \geq 100mm thick welds.
- Support raw FMC data recorded, no need to re-scan.
- 12.1" high-resolution touch screen, can be operated with gloves.
- 7.7kg with 2 batteries, portable and suitable for field work.
- Compatible with SyncScan 2 files, convenient for user's operation.
- Overview (Compatible with SIUI current PAUT/TOFD probes, crawlers.)









TOFD

SIUI



Protection Cover:

- ABS material, more anti-impact.
- Handy switch for easy open and locking, ensures better sealing.




Wireless Transmission



- Wi-Fi is used for SuporUp acquisition software, ensuring real-time data transfer from SyncScan 3 to laptop, convenient and high efficiency.
- If no Wi-Fi on-site, user could insert a SIM card to turn on 4G network, enabling wireless connection anytime and anywhere.
- Access to NDT ultracloud platform. (reserved)

FTFM - Unique TFM Algorithm

- Unique FTFM quad-core algorithm, based on reducing data transmission and computing resources, to achieve fast-speed and high-definition imaging during real-time scanning.
- 9 propagation modes for selection based on the expected defect orientation, to ensure precise defect characterization.
- The envelope processing provides more stable amplitude and reduces noises, which further improves TFM performance.



TFM for PA block type B


TFM for no-fusion defect

FMC – Supports Raw Data Recorded


Raw data can be recorded during full matrix capture (FMC) scanning, allowing users to calculate TFM using more than one propagation mode without the need to re-scan.

• 64 channel PA & 4-ch TOFD – For Demanding Inspections

ullet 64 channel PA provides better coverage and SNR, especially suitable for inspecting \geq 100mm thick materials, complex composite materials, etc.



64-ch PA for PA block type B




64-ch PA image for 5 flaws (Workpiece thickness 168mm)

• Equipped with 4-ch TOFD. With special adapter can convert to TOFD to achieve 5-ch TOFD inspection, suitable for thick weld up to 400mm, with low carbon steel/ alloy steel materials.

Test Wizard – Retain Friendly

- SyncScan 3 continues to adopt step-by-step test wizard to guide users during the whole testing process, retains always friendly experience.
- Easier focus law setup: Usually user can go to Beam Coverage Simulation Wizard to set up the focus law with a few steps. In TFM, user can easily use a ROI (region of interest) to select the beam coverage area.



Technical Specification

*		
	TFM	
Propagation Modes	LL, LLL, LLLL, TT, TTT, TTTT, TLT, TLL, LTT	
Image Resolution	1024×1024, 256×256, 128×128	
Live TFM Envelope	Yes	
No. of Channel	64	
Probe Connector	Tyco, 1 pc	
Max. Supporting Elements	128	
Focusing Mode	Focusing in all points TFM	
FMC Data Acquisition	4096points/channel, 16bit/point	
Pulse Voltage	10-100V, step 10V/20V	
Pulse Width	50-1000ns, step: 10ns	
Gain	0-80dB, step:0.1/0.5/2/6/12dB	
Bandwidth	0.7-20MHz (-3dB)	
A/D Sampling Rate	100MHz/12bit	
Scan Type	A/B/C	
Wizard	Scan wizard	

	Conventional UT	Phased Array	TOFD
No. of Channel	4	System 64	4
Probe Connector	LEMO 00, 8 pcs	Tyco, 1 pc	LEMO 00, 8 pcs(same as UT)
Max. Supporting Elements	8	128	8
PR (Pitch & Catch)	0	Available	8
	N		Nti
Pulser PRF	Negative square	Bi-polar square	Negative square
	Adjustable 10-2000Hz, step: 20Hz	100Hz-10KHz, step: 100/200/500/1000Hz	Adjustable 10-2000Hz, step: 20Hz
Pulse Voltage	50V~400V, min. step 1V	10-100V, step 10V/20V	50V~400V, min. step 1V
Pulse Energy	00.1000	4 levels	
Pulse Width	30-1000ns, step:10ns	50-1000ns, step: 10ns	30-1000ns, step: 10ns
Damping	25/75/200/1000Ω, 4 levels		25/75/200/1000Ω, 4 levels
Pulser Delay	_	0-20μs, resolution 5ns	_
Pulser Focusing	_	Single point focusing	<u> </u>
		Receiver	
Gain	0-110dB, step:0.5/2/6/12dB	0-80dB, step:0.1/0.5/2/6/12dB	0-110dB, step: 0.5/2/6/12dB
Bandwidth	0.5-20MHz (-3dB)	0.7-20MHz (-3dB)	0.5-20MHz (-3dB)
A/D Sampling Rate	170MHz/12bit	100MHz/12bit	170MHz/12bit
Sampling Point	1024, 16bit/ point	Adjustable 256/512/1024, 16bit/point	1024, 16bit/point
Rectification	Positive/ Negative/ Full/ RF	Positive/ Negative/ Full/ Filter/ RF	RF
Receiver Delay	_	0-20μs, resolution 2.5ns	
Receiver Focusing	_	Max. range: 1008 foci per scan line	
	101 1	14 levels: Band-pass:	16 levels:
nut.	10 levels:	0.7-4/2.5-7/4-8.5/7-10/9-15/0.7-20MHz	0.5-5/0.5-10/3.5-10/0.5-15/5-15/
Filter	1-4/0.5-10/2-20/	High-pass: HPF2.5/HPF4.0/HPF7.0/HPF9.0	0.5-20/1-4/0.5-10/2-20/1/2.5/4/5/10/
	1/2.5/4/5/10/13/15MHz	Low-pass: LPF7.0/LPF8.5/LPF10.0/LPF15.0	13/15MHz
Reject	0-80%, step: 1%	<u> </u>	
	•	Scan	
Scan Type	A	A/S/L/C/D	A/ TOFD
Гrigger Mode		Time-based/encoder	Time-based/encoder
Scan Length		≤4m/scan (default parameter, step 0.5mm)	≤50m/scan, 0.5mm/step
Focal Laws		512	
Scan Angle Range		-89°~+89°, step 1°	7 <u></u>
Angle Spacing		0.1°-5°, step 0.1°	
Line Average		0.1 -5 , step 0.1	4 levels, 1/2/4/8
Focus Position	_	3-500mm, step: 1mm	4 levels, 1/2/4/6
A STATE OF THE STA	_	Depth, Sound Path	
Focal Mode		· · · · · · · · · · · · · · · · · · ·	_
	0.15000	Measurement	0.15000
Range	0-15000mm	0-1000mm, min. step 0.01mm,	0-15000mm, min. step 0.1mm,
	Min. display range 5mm	Min. display range 3mm	Min. display range 5mm
Material Velocity	500-15000m/s, min. step:1m/s	500-15000m/s, min. step:1m/s	500-15000m/s, min. step:1m/s
Display Delay	-10-1000mm, min. step: 0.01mm	0-1000mm, min. step: 0.01mm	-10-1000mm, min. step 0.01mm
Probe Zero	0-200us, min. step: 0.01us		0-200us, min. step 0.01us
Probe Flank	0-100mm, step: 0.01mm		0-100mm, step 0.01mm
Test Point Selection	Peak/ Flank/ J Flank/G Flank, G Peak	Peak/ Flank/ J Flank/ G Flank, G Peak	_
Calibration	DAC, AVG/ DGS, Angle calibration,	Scan wizard, velocity/delay/sensitivity/TCG	Scan wizard, PCS Calculation,
	Auto calibration (velocity, zero),	calibration wizard, Zero calibration	Time Window, Probe Zero Calibration
	Plate/ weld/forging scan		Ultrasound Parameter
Curve Function	AVG/DGS; TCG & DAC: Max. 6 lines &	TCG & DAC: Max. 6 lines & 16 points for each	n
Cut ve i unetion	16 points for each line	line	
Auxiliary Function	Coordinates switch (sound path/depth		
	horizontal), full screen, auto freeze,	Auto gain: Single/ Continuous	
	auto gain (single/continuous),	Auto Search: Search the highest echo	
	second leg color, wave compare,	amplitude scan line within gate range in B	10 Th
	gate expansion, wave filling,	scan.(available when in R view)	
	peak envelope, Cineloop, screenshot	1	

Technical Specification

	Conventional UT	Phased Array	TOFD
Auxiliary Function	CrackMeas, API 5UE, AWS, FFT, CSC, TCG, B-Scan, FlatWeldSim, BEA	PA Group: max. 6 groups FlatWeldSim, C Scan In-Depth Probe Element Testing	_
Measurement	Three gates: to measure echo amplitude, amplitude dB difference, sound path, Ra/Da	Three gates for each A scan, max. 18 gates: to measure echo amplitude, sound path, Ra/Da	- Flaw height and length measurement.
	Cursor: two cursors to measure horizontal and vertical position of B scan and distance between cursors.	Cursor: two cursors to measure horizontal and vertical position of B/C/D scan and distance between cursors on B/C/D scan.	
Gate Mode	Normal, Tracing	Sound Path, Depth	_
Gate Start	Full range	Full range	
Gate Width	Full range	Full range	
Gate Thresh	10-90%, step: 1%	10-90%, step: 1%	p
Display Mode	_	A, B, C, D, A+B, B+C, B+D, A+B+C, A+B+D, 3A+B, A+B+C+D, A+B+R, A+B+C+R, A+[B], A+C, full screen.	_
Alarm Signal	Signal&sound alarm: positive/ negative	Signal&sound alarm: positive/ negative	_
Display Measure Value		8 positions can be user-defined.	
Data Analysis	_	Image mode switch, image gate dynamic reconstruction and report generation	LW/BW straightening/ removal, contrast adjust, gain adjust, zoom
		Testing Index	
Time Base Linearity	≤0.5%		
Vertical Linearity	≤3%		_
Amplitude Linearity	≤±2%		I
Attenuator Precision	20dB±1dB		
Dynamic Range	≥32dB		
		Software	
SyncScan 3 Optional Software		PA Flat Weld Solution PA Angle Weld Solution PA Corrosion Solution PA Pipe Girth Weld Solution PA Long Pipe Solution PA Corner Joint Solution	SAFT 1-ch TOFD, 2-ch TOFD 3-ch TOFD, 4-ch TOFD Simultaneous Display of PAUT and TOFD Software
	Analysis Software (Standard)		
SuporUp PC Analysis Software	PA Corrosion Software (Optional)		Two-ways Activation:
	PA Emulator Software (Optional)		*License
	Acquisition Software (Optional)		*Dongle

General Technical Specification		
Display Screen	12.1" high brightness TFT LCD, 1024×768 pixels	
Dimension (W×H×D)	365×270×115 (mm)	
Weight	7.7kg with 2 batteries	
Battery	Lithium batteries, 2 pcs	
Battery Capacity	7.5 Ah/pc, operation time around 3.5 hours	
External Power Supply for Adaptor	AC 100-240V 50Hz/60Hz	
Adaptor Output	15V DC	
Power	52W	
Data Storage	64 GB SSD + Standard SD card (16G)	
Language	English/ German/ French/ Polish/ Czech/ Hungarian	
Input/Output		
USB Connector	2 pcs (3.0)	
Ethernet Connector	1 pc	
Video Output	VGA/ HDMI ports	
Encoder Connector	1 pc (14-core)	
Environment Tests		
Operation Temperature	-10°C-45°C	
Storage Temperature	-20°C-60°C	
IP Code	IP65	
Certifications	ISO 18563-1:2015 & EN12668-1:2010	



Shantou Institute of Ultrasonic Instruments Co., Ltd.

Add: #77, Jinsha Road, Shantou 515041, Guangdong, China Tel: +86-754-88250150 Fax: +86-754-88251499 E-mail: siui@siui.com Website: http://www.siui.com

